Battery Charger

Features

3- step charge control
Switch model
Charge current not affected by fluctuations in main voltage

Wide input voltage range
Having system LED function
Short circuit / over load / over current protection

Model	C1202	C1204	C1206	C2405	C3602	C4825	C1208	C2406	C1210A	C1215B
Input voltage range	110/220(-10%--+25%)choice						*110/220(-10%--+25%)choice*			
Input frequency range	47-63Hz	47-63Hz	47-63Hz	47-63Hz	47-63Hz	47-63Hz	47-63Hz	47-63Hz	47-63Hz	47-63Hz
Charging way	3-step charge control switch mode						3-step charge control switch mode			
output voltage of constant current	13.7□0.3Vdc	13.7□0.3Vdc	13.7□0.3Vdc	27.5□0.3Vdc	27.5□0.3Vdc	54.8□0.3Vdc	13.7□0.3Vdc	27.5□0.3Vdc	13.7□0.3Vdc	13.7□0.3Vdc
	_	_	_	_	_	_	_	_	_	_
Protection	*Short-circuit/over-load/over-current protection*						*Short-circuit/over-load/over-current/ over temperature/reverse polarity*		Short-circuit/over-load/over-current protection	